

# AVR RELAY

MONOFAZIC

Stabilizatoare AVR pe relee de putere medie.

2000VA | 3000VA | 5000VA | 10000VA

1200W

1800W

3000W

6000W



## Carcateristici

Carcasa metalica  
4x picioare pentru aderenta crescuta / anti-zgarriere  
1x maner pentru manipulare usoara / transport  
Transformator toroidal de inalta calitate  
MCU Control Circuit = Tensiune iesire stabila  
Technologie 0 Cross Transfer



**Iesiri**  
2x Schuko  
1x Regleta



**Precizie**  
8-10%



**Timp Delay**  
selectabil  
6s / 180s



**Display Digital**  
tensiune in/out  
erori & protectii  
nivel sarcina



**Tehnologie**  
Transformator toroidal  
MCU Control Circuit



**Protectie**  
Komplet 6: suprasarcina, supra/sub-tensiune,  
supraincalzire, scurt-circuit, alarma sonora, IP20

## APLICATII AVR RELAY



**ELECTRO  
CASNICE  
MICI**



**PC  
LAPTOP**



**APARATURA  
AUDIO  
VIDEO**



**CENTRALE  
TERMICE**

## SPECIFICATII TEHNICE



	2000VA	3000VA	5000VA	10000VA
Putere	1200W	1800W	3000W	6000W
Tensiune / Frecventa intrare	140-260V AC / 45-65Hz			
Tensiune / Frecventa iesire	230V ± 8-10% / 50Hz			
Conectori iesire	2x Schuko	2x Schuko + Regleta		
Unda / Eficienta	sinusoidala pura / 98%			
Timp de Intarziere	6s / 180s selectabil			
Dimensiuni (L x l x h)	146 x 237 x 170 mm	190 x 285 x 202 mm	285 x 190 x 202 mm	333 x 220 x 230 mm
Greutate	4.1kg	6.5kg	7.2kg	23.2kg
Nivel zgomot	< 20dB (la 1m distanta)			
Temperatura functionare	0°C - 40°C			
Umiditate functionare	20-90% fara condens			