



мсв ВКН ВКР BF-a BF-c BFN Overload and short circuit Overload and short circuit | Overload and short circuit Overload and short circuit 63, 80, 100, 125A 3, 6, 10, 16, 20, 25, 32A 10~100A 5, 10, 15, 20, 30, 40, 50A C, D curve B, C, D curve 1P, 2P, 3P 1P, 2P, 3P 1p, 2p, 3p, 3p+N, 4p 1p+N 1pole 1pole 2~4pole 2~3pole 10A~100A 10A~100A 63A~125A 3A~32A 63A~125A 10kA at 5kA at 5A~50A 5A~50A 10kA at 4.5kA at 10kA at 240VAC 240VAC 10kA at 10kA at 230/400 230VAC 400VAC 2.5kA a 2.5kA at 230VAC 400VAC VAC (NF: 3kA) 415VAC 415VAC IEC 60947-2 IEC 60947-2 IEC 60898 IEC 60947-2 CCC, SEMKO CB, SABS, CE CCC, SEMKO CB, NF, SABS, CE SEMKO CB, CE Thermal magnetic release Thermal magnetic release Thermal magnetic release Thermal magnetic release 4,000 operations 1,500 operations 1,500 operations 1,500 operations 10,000 operations 10,000 operations 10,000 operations 10,000 operations On 35mm DIN rail On 35mm DIN rail Holder mounting (Bolt on with fixing brackets) Plug-in 27mm per pole 17.8mm per pole 25mm per pole 25mm per pole Lug type (14-6 AWG.) Lug type(cable up to 50mm²) Lug type(cable up to 10mm²) Clamp type See drawing 3 See drawing 4 See drawing 5 See drawing 6

Curve 1: Type BKN, BKN-b, BKN-c, BKH, BKP, RKP, RKS




Curve 2: Type BFN



Drawing 4 : Type BKP


See curve 1




See curve 1

Drawing 5: Type BF-a, BF-c

See curve 2



Drawing 6: Type BFN



Miniature circuit breakers

DIN rail mounting

(€ 4500

BKP type



BKP 1P+N

<u>Certificate</u> CE

Technical data

Standard	Confirming to IEC60898			
Approval	CCC, CQC CB			
Protection	Overload and short circuit			
Rated current In	3, 6, 10, 16, 20, 25, 32A			
Rated voltage	230VAC			
Breaking capacity	4.5kA			
Characteristic	B, C, D curve			
Number of poles	1P+N			
Type of trip	Thermal magnetic release			
Type of terminal	Lug type			
Terminal capacity	Cables up to 10mm ²			
Installation	Mounting on 35mm DIN rail			
Width	17.8mm per pole			
Electrical endurance	20000 cycles			

Catalog No.

Pole	Туре	In	Model	Catalog No.	Pack. unit (Pcs.)	PRICE
1P+N	B curve	ЗА	BKP B3A	06120302R0	120	
		6A	BKP B6A	06120228R0	120	
		10A	BKP B10A	06120229R0	120	
		16A	BKP B16A	06120230R0	120	
		20A	BKP B20A	06120231R0	120	
		25A	BKP B25A	06120303R0	120	
		32A	BKP B32A	06120232R0	120	
	C curve	ЗА	BKP C3A	06120307R0	120	
		6A	BKP C6A	06120235R0	120	
		10A	BKP C10A	06120236R0	120	
		16A	BKP C16A	06120237R0	120	
		20A	BKP C20A	06120238R0	120	
		25A	BKP C25A	06120309R0	120	
		32A	BKP C32A	06120239R0	120	
	D curve	ЗА	BKP D3A	06120308R0	120	
		6A	BKP D6A	06120242R0	120	
		10A	BKP D10A	06120243R0	120	
		16A	BKP D16A	06120244R0	120	
		20A	BKP D20A	06120245R0	120	
		25A	BKP D25A	06120311R0	120	
		32A	BKP D32A	06120246R0	120	